


MCX103B,D Hall Effect Rotary Position Sensor

Technical Information





## SAUER Technical Information MCX103B,D Hall Effect Rotary Position Sensor **Technical Information** Contents

#### **PRODUCT OVERVIEW**

Description	3
DescriptionFeatures	3
Ordering information	3
Specify	3
Part number quick reference	3
Technical data	
Electrical	4
Electrical data	4
Environmental	4
Theory of operation	4
Sensor supply voltage	4
Dimensions	5
MCX103B with 45° sensor range	
MCX103B with 90° sensor range	
MCX103D	6

#### **PRODUCT INSTALLATION**

Installation	
Mounting	
Wiring	

© 2004 Sauer-Danfoss. All rights reserved. Printed in U.S.A.

Sauer-Danfoss accepts no responsibility for possible errors in catalogs, brochures and other printed material. Sauer-Danfoss reserves the right to alter its products without prior notice. This also applies to products already ordered provided that such alterations aren't in conflict with agreed specifications. All trademarks in this material are properties of their respective owners. Sauer-Danfoss and the Sauer-Danfoss logotype are trademarks of the Sauer-Danfoss Group.

Front cover illustrations: 2229; 2230 2231; 2232; 2233



### SAUER Technical information MCX103B,D Hall Effect Rotary Position Sensor **Technical Information** Product overview

#### **DESCRIPTION**

The MCX103 Hall Effect Rotary Position Sensor serves as either a command (when connected to a control handle, foot pedal, throttle, steering wheel, etc.) or feedback source.

Housed in aluminum, the MCX103 contains a non-contacting linear hall effect sensor with an input shaft supported by a sleeve bearing.

#### **FEATURES**

- Non-contact sensor withstands high shock and vibration
- Input voltage adapted for microprocessor circuits
- Infinite resolution
- Long life
- Designed to withstand the mobile environment
  - -40° to 85° C operating range
  - 95% relative humidity
  - Meets off-highway vibration standards
  - Protected against static discharge, EMI and RFI

#### **ORDERING INFORMATION**

#### Specify

- 1. Part number MCX103B or MCX103D. See Part number quick reference.
- 2. Flange mount.
- 3. Rotation angle.

#### Part number quick reference

Part Number	Supply Voltage	Total Mechanical Rotation	Total Electrical Rotation	Body Style	Flats on shaft	Connection Type	Cable Length
MCX103B1043	5 Volt	300°	45°	Round housing	15,75 (.62) Dual	Metri-Pack	12 ± 1
MCX103B1050	5 Volt	300°	90°	Round housing	15,75 (.62) Dual	Metri-Pack	12 ± 1
MCX103B1076	5 Volt	300°	45°	Round housing	15,75 (.62) Dual	Weather Pack	12 ± 1
MCX103B1084	5 Volt	300°	90°	Round housing	15,75 (.62) Dual	Weather Pack	12 ± 1
MCX103B1145	5 Volt	300°	45°	Round housing	11,94 (.47) Dual	Weather Pack	12 ± 1
MCX103B1153	5 Volt	300°	90°	Round housing	11,94 (.47) Dual	Weather Pack	12 ± 1
MCX103B1161	5 Volt	300°	45°	Round housing	15,75 (.62) Dual	Metri-Pack	3 ± 1
MCX103D1017	8 Volt	360°	90°	Round housing w/flange	12,7 (.50) Single	Weather Pack	12 ± 1
MCX103D1025	8 Volt	360°	90°	Round housing w/flange	12,7 (.50) Single	Deutsch	12 ± 1
MCX103D1033	8 Volt	360°	90°	Round housing w/flange	12,7 (.50) Single	Deutsch w/gold contacts	12 ± 1

# Technical Information MCX103B,D Hall Effect Rotary Position Sensor Product overview

#### **TECHNICAL DATA**

#### **Electrical**

Electrical data

ı	n	p	ut	vo	lta	q	(

5.0 to 8.0 V DC

#### Hall effect electromagnetic sensor

Life is not limited by the number of cycles

#### **Maximum output load current**

1 mA sourcing or sinking

#### **Maximum current draw**

20 mA

#### **Output impedance**

0

#### Input torque

Not to exceed 25 oz•in

#### Side loading

One million cycles with 5 pound side load

#### Hysteresis

Negligible

#### Linearity

Approximately  $\pm 3\%$  over the rated angle. Since the output is proportional to the sine of the input angle, greater linearity can be achieved by reducing the angle employed.

#### **Temperature rating**

-40° to 85° C (-40° to 185° F) operating

-55° to 125° C (-67° to 257° F) storage

#### **Temperature stability**

Null shift of  $\pm .028\%$  per °C from -40° to 85° C


Gain shift of ±.025% per °C from -40° to 85° C

#### **Environmental**

The MCX103 has been tested and qualified to Sauer-Danfoss environmental specifications, designed for mobile equipment applications. The test includes vibration, shock, EMI/RFI, short circuit, over voltage, humidity, high pressure wash down, and chemical resistance.

#### THEORY OF OPERATION

A "U" shaped magnet is mounted to the input shaft of the MCX103. Mounted in a fixed position between the north and south poles of the magnet is a linear hall effect senor. As the "U" shaped magnet is rotated, the changing magnetic flux lines cutting through the hall effect sensor cause the output to change linearly from 25 to 75% of supply voltage for 90° Sensors. The output changes from 30 to 70% of supply voltage for 45° sensors.






# SAUER Technical Information MCX103B,D Hall Effect Rotary Position Sensor **Product overview**

#### **DIMENSIONS**

Dimensions of the MCX103B with 45° sensor range in millimeters [inches].






## **Technical Information** MCX103B,D Hall Effect Rotary Position Sensor


#### **Product overview**

#### **DIMENSIONS**

Dimensions of the MCX103B with 90° sensor range in millimeters [inches].



#### Dimensions of the MCX103D in millimeters [inches].





## **Technical Information** MCX103B,D Hall Effect Rotary Position Sensor **Product Installation**

#### **INSTALLATION**

#### Mounting

The MCX103B has four 6M x 1M threaded holes on the face of the input shaft end of the sensor.

The MCX103D has a mounting flange, with four slotted holes.

See Dimensions, pages 5 and 6.

#### Wiring

Electromagnetic and radio frequency interference (EMI/RFI) will be present in varying degrees in any environment that has static electricity, power lines, radio equipment, solenoid switching, etc. To avoid the harmful effects of EMI/RFI, use braided (not foil) shield cables with a minimum of 75% shielding. Terminate the shield at both ends to the connector shell with as short a length as possible. All electrical connections are made to the sensor through a three-pin sealed connector: Pin A (supply voltage), Pin B (output), and Pin C (ground). See Dimensions, pages 5 and 6.



#### Caution

Reverse polarity may damage the sensor.

Mating connectors can be ordered from Sauer-Danfoss, part number K10309 (Metri-Pack) or part number K08620 (Weather Pack). Part number K22335 (Deutsch) or part number 10103018 (Deutsch w/gold contacts).



#### **Our Products**

Open circuit axial piston pumps

Gear pumps and motors

Fan drive systems

Closed circuit axial piston pumps and motors

Bent axis motors

Hydrostatic transmissions

Transit mixer drives

Hydrostatic transaxles

Electrohydraulics

Integrated systems

Microcontrollers and software

PLUS+1™ GUIDE

Displays

Joysticks and control handles

Sensors

Orbital motors

Inverters

Electrohydraulic power steering

Hydraulic power steering

Hydraulic integrated circuits (HIC)

Cartridge valves

Directional spool valves

Proportional valves

# Sauer-Danfoss Mobile Power and Control Systems – Market Leaders Worldwide

Sauer-Danfoss is a comprehensive supplier providing complete systems to the global mobile market.

Sauer-Danfoss serves markets such as agriculture, construction, road building, material handling, municipal, forestry, turf care, and many others.

We offer our customers optimum solutions for their needs and develop new products and systems in close cooperation and partnership with them.

Sauer-Danfoss specializes in integrating a full range of system components to provide vehicle designers with the most advanced total system design.

Sauer-Danfoss provides comprehensive worldwide service for its products through an extensive network of Global Service Partners strategically located in all parts of the world.

Local address:			

 Sauer-Danfoss (US) Company
 Sauer-Danfoss ApS

 2800 East 13th Street
 DK-6430 Nordborg, Denmark

 Ames, IA 50010, USA
 Phone: +45 7488 4444

 Phone: +1 515 239-6000
 Fax: +45 7488 4400

 Fax: +1 515 239 6618

Sauer-Danfoss GmbH & Co. OHG Shin-Osaka TERASAKI 3rd Bldg. 6F Postfach 2460, D-24531 Neumünster 1-5-28 Nishimiyahara, Yodogawa-ku Krokamp 35, D-24539 Neumünster, Germany Osaka 532-0004, Japan

Phone: +49 4321 871 -0 Phone: +81 6 6395 6066
Fax: +49 4321 871 122 Fax: +81 6 6395 8585